

The Evans function: An example

Consider the scalar partial differential equation (PDE)

$$u_t = u_{xx} - u + u^3, \quad u \in \mathbb{R}, \quad x \in \mathbb{R} \quad (1)$$

which has the stationary solution $u(x, t) = q(x) := \sqrt{2} \operatorname{sech} x$.

Linearizing of (1) about $q(x)$ gives the linear PDE

$$u_t = u_{xx} + (3q(x)^2 - 1)u$$

or

$$u_t = u_{xx} + (6 \operatorname{sech}^2(x) - 1)u.$$

The essential spectrum is given by

$$\Sigma_{\text{rm}} = \{\lambda \in \mathbb{C}; \lambda = -k^2 - 1 \text{ for } k \in \mathbb{R}\}$$

The eigenvalue problem associated with the linearization about the pulse q is given by

$$\lambda u = u_{xx} + (6 \operatorname{sech}^2(x) - 1)u, \quad (2)$$

which we shall also write as the linear first-order differential equation

$$\begin{pmatrix} u_x \\ v_x \end{pmatrix} = \begin{pmatrix} 0 & 1 \\ 1 + \lambda - 6 \operatorname{sech}^2(x) & 0 \end{pmatrix} \begin{pmatrix} u \\ v \end{pmatrix}. \quad (3)$$

To construct the Evans function, we need to find solutions of (2) or (3) that decay to zero as $x \rightarrow \infty$ or as $x \rightarrow -\infty$.

Using hypergeometric series, these solutions are found to be

$$u_-(x; \lambda) = e^{\sqrt{1+\lambda}x} \left[1 + \frac{\lambda}{3} - \sqrt{1+\lambda} \tanh(x) - \operatorname{sech}^2(x) \right],$$

which decays to 0 as $x \rightarrow -\infty$ for $\operatorname{Re} \lambda > -1$, and

$$u_+(x; \lambda) = e^{-\sqrt{1+\lambda}x} \left[1 + \frac{\lambda}{3} + \sqrt{1+\lambda} \tanh(x) - \operatorname{sech}^2(x) \right]$$

which decays to 0 as $x \rightarrow \infty$ for $\operatorname{Re} \lambda > -1$.

The Evans function $E(\lambda)$ is defined to be the Wronskian

$$E(\lambda) = \det \begin{pmatrix} u_-(0; \lambda) & u_+(0; \lambda) \\ u'_-(0; \lambda) & u'_+(0; \lambda) \end{pmatrix} = -\frac{2}{9} \lambda (\lambda - 3) \sqrt{1 + \lambda} \quad (4)$$

of the two solutions $u_{\pm}(x; \lambda)$.

By construction, a complex number λ is a root of the Evans function precisely when (2) and (3) have a bounded nonzero solution for that value of λ : indeed, the solutions $u_-(x; \lambda)$ and $u_+(x; \lambda)$ are then linearly dependent and generate a bounded nonzero solution of (2).

Thus, the spectrum is given by

